

QR, AZTEC and barcode scanner with charging station, WiFi Bluetooth reader with built-in memory, USB HD-LR66

SKU: HD-LR66 | EAN: 5907614664343



Scanning method: manually (via button) / automatically (when code is near)

Types of codes read: 1D and 2D barcodes, including QR and Aztec, from paper labels and phone screens

Wireless communication: Bluetooth, 2.4 G

Built-in memory: yes

QR, AZTEC and barcode scanner with charging station, WiFi Bluetooth reader with built-in memory, USB HD-LR66

Model	HD-LR66	Light source	617nm LED
Scanning method	automatically (after approaching the code), manually (push button)	Confirmation of scanning	light and sound signal
Scanning speed	300 scans/second	Wireless communication	2.4 G, bluetooth
Interface	USB	Drop resistance	up to 1.5 metres
Dimensions of the device	18 x 14.5 x 9.5 cm	Package dimensions	18 x 14.5 x 9.5 cm
Weight	450 g	Weight with packaging	525 g
Operating temperature	-20 - 50°C	Storage temperature	-30 - 60°C
Readable 1D codes	CODABAR, CODE 11, CODE 128, CODE 32, Code 39Full ASCII, CODE 93, Code39, GS1 DataBar, Industrial 2 of 5, Interleaved 2 of 5 (ITF), ISBN, ISSN, MSI, UPC/EAN	Readable 2D codes	Aztec, Datamatrix, HanXin, MaxiCode, MicroPDF417, microQR, QR Code

